



## **Model 607A11/030AC**

**Low profile industrial ICP® accel, 100 mV/g, 0.5 to 10k Hz, side exit, 30-ft integral cable to BNC plug & swiveler base**

### **Installation and Operating Manual**

**For assistance with the operation of this product,  
contact the PCB Piezotronics, Inc.**

**Toll-free: 800-959-4464  
24-hour SensorLine: 716-684-0001  
Fax: 716-684-3823  
E-mail: [imi@pcb.com](mailto:imi@pcb.com)  
Web: [www.imi-sensors.com](http://www.imi-sensors.com)**





**INDUSTRIAL MONITORING INSTRUMENTATION DIVISION**

## **Piezoelectric ICP® Accelerometers Operating Guide**

---

### ***Operating Guide with Enclosed Warranty Information***

---

***3424 Walden Avenue, Depew, New York 14043-2495***

***Phone (716) 684-0003***

***Fax (716) 684-3823***

***Toll Free Line 1-800-959-4IMI***

***MANUAL NUMBER: 18405***

***MANUAL REVISION: A***

***ECN NUMBER: 49766***



## General OPERATING GUIDE

for use with

### PIEZOELECTRIC ICP® ACCELEROMETERS

SPECIFICATION SHEET, INSTALLATION DRAWING AND CALIBRATION INFORMATION ENCLOSED

IMI ASSUMES NO RESPONSIBILITY FOR DAMAGE CAUSED TO THIS PRODUCT AS A RESULT OF PROCEDURES THAT ARE INCONSISTENT WITH THIS OPERATING GUIDE

#### 1.0 INTRODUCTION

Congratulations on the purchase of a quality ICP® industrial sensor. In order to ensure the highest level of performance for this product, it is imperative that you properly familiarize yourself with the correct mounting and installation techniques before attempting to operate this device. If, after reading this manual, you have any additional questions concerning this sensor or its application, feel free to call an Application Engineer at **716-684-0003** or **800-959-4464**.

Proper sensor selection requires special attention to three main areas: sensor design, dynamic expectations, and application environment.

Sensor design encompasses the actual sensing element, the physical material, and component selection for the sensor. Preferred industrial accelerometers employ a shear sensing element with either a quartz or ceramic crystal.

Quartz sensing elements are typically used when long-term stability and minimum output shifts due to temperature changes are desired. Ceramic sensing elements provide excellent resolution and durability in noisy environments, and can be designed to supply low-frequency and high-frequency measurements. Shear-design sensors are preferred because of their inherent insensitivity to adverse environmental influences, such as case or base strain and thermal transients. Internal case isolation and shielding is important in avoiding erroneous signals resulting from ground loops and pick-up of electromagnetic and radio frequency interference. Other critical material selection criteria include non-magnetic stainless steel housing, hermetic sealing, and industrial military connectors. See Figure 1.




Figure 1. Typical Industrial Shear Mode Accelerometer

Dynamic expectations are application-specific and refer to the frequency range of measurement and the anticipated amplitudes of vibration. After careful review of the machinery to be monitored, minimum and maximum measurement frequency ranges may be established. The minimum measurement frequency is normally related to any sub-harmonics of running speed or any lower frequencies where vibration data is to be collected. The maximum measurement frequency of interest is determined by the maximum number of harmonics of an event like running speed, bearing frequencies, or gear mesh. This measurement frequency range should be well within the specified frequency range of the sensor.


Amplitude range refers to the anticipated levels of vibration to be measured. These values are related to the alarm levels set for the machine. By carefully evaluating the idiosyncrasies of the machinery, the predictive maintenance engineer can estimate the minimum expected vibration levels and ensure that the electrical noise floor of the accelerometer is less than those levels.

The environment of the application is a critical consideration during program implementation. The sensor chosen must be capable of surviving the wide range of conditions to which it is subjected; therefore, take time to evaluate potential conditions, such as high temperatures and chemical contaminants. The specified temperature range of the sensor must conform to the fluctuations of the environmental temperature. If harsh industrial chemicals are present, the sensor requires hermetic sealing and construction that resists corrosion. Finally, specific location of the sensor within the environment must be sensible, as both cable and sensor may be damaged by imprudent installation in heavily traveled, physically punishing areas.

## 2.0 ICP® ACCELEROMETERS

Enclosed in the back of this guide is a Specification Sheet, which lists the complete performance characteristics of the particular sensor.

All ICP® sensors require a constant current power source for proper operation. A typical sensing system includes an ICP® sensor, ordinary two conductor cable and a basic constant current power supply (as shown in Figure 2).




**Figure 2. Typical Sensor System**

The signal conditioner consists of a well-regulated 18 to 30 VDC source (battery or line-powered), a current-regulating diode (or equivalent constant current circuit), and a capacitor for decoupling (removing the bias voltage) the signal.

The current-regulating device is used in place of a resistor for several reasons. The very high dynamic resistance of the diode yields a source follower gain which is extremely close to unity and independent of

input voltage. Also, the diode can be changed to supply higher currents for driving long cable lengths. Constant current diodes, as shown in Figure 3, should be used in ICP® signal conditioners. **(The correct orientation of the diode within the circuit is critical for proper operation.)** Except for special models, standard ICP® sensors require a minimum of 2 mA for proper operation.



**Figure 3. Constant Current Diode**

The typical limits for this type of diode are to a 4 mA maximum rating; however, several diodes can be placed in parallel for higher current levels. All line-powered signal conditioners should use higher capacity (up to 20 mA) constant current circuits in place of the diodes, particularly when driving long signal cables (see Section 5).

Decoupling of the data signal occurs at the output stage of the signal conditioner. A 10 to 30 µF capacitor coupled with a resistor shifts the signal level to essentially eliminate the sensor bias voltage. The result is a drift-free AC mode of operation.

## 3.0 OPTIONAL FEATURES

In addition to standard features, a variety of options are also available. When listed before the model number, the following prefix letters indicate that the sensor is manufactured or supplied with optional features:

- CS - Canadian Standards Association Approved Sensor
- D - Dummy, non-working sensor for display purposes
- EX - Cenelec Approved Sensor
- FM - Factory Mutual Approval Sensor
- HT - High temperature accelerometer (325 °F)
- LB - Low Bias electronics
- LC - Limited Calibration (one point calibration)
- LP - Low Pass filter
- M - Metric mounting hardware and cable length
- U - Usable demonstration sensor (does not meet one or more minor specifications)
- VO - Velocity Output Sensors

MS – Mine Safety Approved Sensors  
TO – Temperature Output Sensor


**Note:** *Not all sensors are available with the optional prefixes. Contact the factory to discuss special features that may be needed.*

## 4.0 INSTALLATION OVERVIEW

When choosing a mounting method, consider closely both the advantages and disadvantages of each technique. Characteristics like location, ruggedness, amplitude range, accessibility, temperature, and portability are extremely critical. However, the most important and often overlooked consideration is the effect the mounting technique has on the high-frequency operating range of the accelerometer.

Shown in Figure 4 are six possible mounting techniques and their effects on the performance of a typical piezoelectric accelerometer. (**Note:** *Not all of the mounting methods may apply to your particular sensor.*) The mounting configurations and corresponding graph demonstrate how the high-frequency response of the accelerometer may be compromised as mass is added to the system and/or the mounting stiffness is reduced.

**Note:** *The low-frequency response is unaffected by the mounting technique. This roll-off behavior is typically fixed by the sensor's built-in electronics. However, when operating AC-coupled signal conditioners with readout devices having an input impedance of less than one megaohm, the low frequency range may be affected.*




**Figure 4.** Assorted Mounting Configurations and Their Effects on High Frequency

## 4.1 STANDARD STUD MOUNT

This mounting technique requires smooth, flat contact surfaces for proper operation and is recommended for permanent and/or secure installations. Stud mounting is also recommended when testing at high frequencies.

**Note:** *Do NOT attempt mounting on curved, rough, or uneven surfaces, as the potential for misalignment and limited contact surface may significantly reduce the sensor's upper operating frequency range.*




|                | 1/4-28 Stud | 1/4-28 Captive Screw |
|----------------|-------------|----------------------|
| A (in.)        | .250        | .250                 |
| B (in.)        | .350        | .350                 |
| Torque (ft-lb) | 2 to 5      | 2 to 5               |

**Figure 5.** Mounting Surface Preparation

**STEP 1:** First, prepare a smooth, flat mounting surface and then drill and tap a mounting hole in the center of this area as shown in Figure 5.

A precision-machined mounting surface with a minimum finish of 63  $\mu$ in (0.0016 mm) is recommended. (If it is not possible to properly prepare the machine surface, consider using an adhesive mounting pad as a possible alternative.) Inspect the area, checking that there are no burrs or other foreign particles interfering with the contact surface.

**STEP 2:** Wipe clean the mounting surface and spread on a light film of grease, oil, or similar coupling fluid prior to installation. See Figure 6.



**Figure 6.** Mounting Surface Lubrication

Adding a coupling fluid improves vibration transmissibility by filling small voids in the mounting surface and increasing the mounting stiffness. For

semi-permanent mounting, substitute epoxy or another type of adhesive.

**STEP 3:** Hand-tighten the sensor/mounting stud to the machine, then secure the sensor with a torque wrench to the mounting surface by applying the recommended mounting torque. (See enclosed specification data sheet for proper mounting torque.)

It is important to use a torque wrench during this step. Under-torqueing the sensor may not adequately couple the device; over-torqueing may result in stud failure and possibly permanent damage.

#### 4.2 ADHESIVE MOUNT

Adhesive mounting is often used for temporary installation or when the machine surface cannot be adequately prepared for stud mounting. Adhesives like hot glue or wax work well for temporary mounts; two-part epoxies and quick-bonding gels provide a more permanent mount.

**Note:** *Adhesively-mounted sensors often exhibit a reduction in high-frequency range. Generally, smooth surfaces and stiff adhesives provide the best frequency response. Contact the factory for recommended epoxies.*

##### METHOD 1 – Adhesive mounting base

This method involves attaching a base to the machine surface, then securing the sensor to the base. This allows for easy removal of the accelerometer.

**STEP 1:** Prepare a smooth, flat mounting surface. A minimum surface finish of 63  $\mu\text{in}$  (0.0016 mm) generally works best.

**STEP 2:** Stud-mount the sensor to the appropriate adhesive mounting base according to the guidelines set forth in **STEPS 2** and **3** of the Stud Mount Procedure.

**STEP 3:** Place a small portion of adhesive on the underside of the mounting base. Firmly press down on the assembly to displace any extra adhesive remaining under the base. See Figure 7.




Figure 7. Mounting Base: Adhesive Installation

##### METHOD 2 – Direct Adhesive Mount

For restrictions of space or for convenience, most sensors (with the exception of integral stud models) can be adhesive-mounted directly to the machine surface.

**STEP 1:** Prepare a smooth, flat mounting surface. A minimum surface finish of 63  $\mu\text{in}$  (0.0016 mm) generally works best.

**STEP 2:** Place a small portion of adhesive on the underside of the sensor. Firmly press down on the top of the assembly to displace any adhesive. Be aware that excessive amounts of adhesive can make sensor removal difficult. See Figure 8.




Figure 8. Direct Adhesive Mounting

#### 4.3 MAGNETIC MOUNT

Magnetic mounting provides a convenient means for making portable measurements and is commonly used for machinery monitoring and other portable or trending applications.

**Note:** *The correct magnet choice and an adequately prepared mounting surface are critical for obtaining reliable measurements, especially at high frequencies. Poor installations can cause as much as a 50% drop in the sensor frequency range.*

Not every magnet is suitable for all applications. For example, rare earth magnets are commonly used because of their high strength. Flat magnets work well on smooth, flat surfaces, while dual-rail magnets are required for curved surfaces. In the case of non-magnetic or rough surfaces, it is recommended that the user first weld, epoxy, or otherwise adhere a steel mounting pad to the test surface. This provides a smooth and repeatable location for mounting.

**STEP 1:** After choosing the correct magnet type, inspect the unit, verifying that the mounting surfaces are flat and smooth. See Figure 9.




Figure 9. Magnet Types

**STEP 2:** Stud-mount the accelerometer to the appropriate magnet according to the guidelines set forth in **STEPS 2** and **3** of the Stud Mount Procedure.

**STEP 3:** Prepare a smooth, flat mounting surface. A minimum surface finish of 63  $\mu$ in (0.0016 mm) generally works best. After cleaning the surface and checking for burrs, wipe on a light film of silicone grease, machine oil, or similar-type coupling fluid.

**STEP 4:** Mount the magnet/sensor assembly to the prepared test surface by gently “rocking” or “sliding” it into place. See Figure 10.




Figure 10. Magnet Mounting

**Note:** *Magnetically mounting accelerometers carelessly has the potential to generate very high (and very damaging) g levels. To prevent damage, install the assembly gently. If unsure, please contact the factory for assistance.*

#### 4.4 HANDHELD OR PROBE TIP MOUNT

This method is NOT recommended for most applications. It is generally used where access to machinery may be a safety concern. Both the accuracy and repeatability at low (<5 Hz) and high frequency (>1 kHz) ranges are questionable.

#### 5.0 CABLING

The selection of connectors and cables has a direct impact on the ruggedness and reliability of the sensor installation. A consideration when dealing with cables is the way in which the cable conductors are terminated.

ICP® accelerometers are internally amplified, two-wire accelerometers. Connections to the sensor require two leads: one for the power and signal, and the other for the common and signal return. Often, coaxial cables are used since only two conductors are needed. Coaxial cables are less expensive. With coaxial cables, however, erroneous signals can be introduced into sensor systems through ground loops, electromagnetic interference, or radio frequency interference (EMI or RFI). To avoid ground loops, there should only be one ground in the system.

It is recommended for permanent installations that the sensor be case-isolated and internally shielded with a dual-case design and use a two-conductor shielded cable to insure clean vibration signal transmission. Two-conductor shielded cables allow the signal and the signal return (common) to be fully shielded from the sensor to the readout equipment. To insure that ground loop signals are not induced, the shield should only be terminated at one end. Typically, the shield of a two-conductor shielded cable is left open or not connected at the sensor end and is tied to earth ground at the instrumentation end.

Operation over long cables may affect the frequency response of ICP® accelerometers, and introduce low frequency noise and high frequency distortion when an insufficient current is available to drive cable capacitance.

Unlike charge mode systems, where the system noise is a function of cable length, ICP® sensors provide a high voltage, low impedance output well-suited for driving long cables through harsh environments. While there is virtually no increase in noise with ICP® sensors, the capacitive loading of the longer cable may be distort or filter higher frequency signals depending on the supply current and the output impedance of the sensor.

Generally, this signal distortion is not a problem with lower frequency testing within a range up to 1,000 Hz. However, when monitoring higher frequency vibrations traveling over cables longer than 500ft, the possibility of signal distortion exists.

The maximum frequency that can be transmitted over a given cable length is a function of both the cable capacitance and the ratio of the peak signal voltage to the current available from the signal conditioner according to:



$$f_{\max} = \frac{10^9}{2\pi CV} \quad (\text{Equation 1})$$

[L<sub>c</sub>-1]

Where,  $f_{\max}$  = maximum frequency (hertz)  
C = cable capacitance (picofarads)  
V = maximum peak output from sensor (volts)  
 $L_c$  = constant current from signal conditioner (mA)  
 $10^9$  = scaling factor to equate units

Note that in this equation, 1 mA is subtracted from the total current supplied to sensor ( $L_c$ ). This is done to compensate for powering the internal electronics. Also, note that these are typical values only.

When driving long cables, Equation 1 shows that, as the length of the cable, peak voltage output or maximum frequency of interest increases, a greater constant current will be required to drive the signal.

The nomograph on page 12 of this manual provides a simple, graphical method for obtaining the expected maximum frequency capability of an ICP® measurement system. The maximum peak signal voltage amplitude, cable capacitance and supplied constant current must be known or presumed.

For example, when running at 100 ft (30.5 m) cable with a capacitance of 30 pF/ft, the total capacitance is 3,000pF. This value can be found along the diagonal cable capacitance lines. Assuming the sensor operates at a maximum output range of 5 volts and the constant current available from the power supply is 2 mA, the ratio on the vertical axis can be calculated to equal 5. The intersection of the total cable capacitance and this ratio result in a maximum frequency of approximately 10.2 kHz.

The nomograph does not indicate whether the frequency amplitude response at a point is flat, rising or falling. For precautionary reasons, it is good general practice to increase the constant current (if possible) to the sensor (within its maximum limit) so that the frequency determined from the nomograph is approximately 1.5 to 2 times greater than the maximum frequency of interest.

**Note:** Higher current levels will deplete battery-powered signal conditioners at a faster rate. Also, any current not used by the cable goes directly to power the internal electronics and will create heat. This may cause the sensor to

exceed its maximum temperature specification. For this reason, do not supply excessive current over short cable runs or when testing at elevated temperatures.

### 5.1 CABLE CONNECTOR PROCEDURE

Care and attention to installation is essential, as the reliability and accuracy of your system is no better than that of the output cable.

**STEP 1:** Ascertain that you have ordered the correct cable type.

As with sensors, no cable can satisfy all applications. Special low-noise cabling should be used with high impedance, charge-output devices. ICP® sensors usually operate with any ordinary tow-wire cable. Industrial applications often require twisted/shielded cables to reduce the effects of EMI and RFI. PTFE-jacketed cabling may be necessary to withstand corrosive environments.

**STEP 2:** Connect the cable to the accelerometer. A small amount of thread-locking compound placed on the connector prior to attachment helps secure the cable during testing. In harsh environments, the connection can be sealed with silicone rubber, O-rings, and flexible heat-shrink tubing.

**STEP 3:** Plug the connector of the cable into the mating sensor connector. Then, holding the sensor stationary, secure the connector in place by tightening down the attached threaded cable sleeve.


**STEP 4:** Route the cable to the signal conditioner, making certain to stress-relieve the sensor/cable connection and minimize motion by clamping the cable at regular intervals.

Common sense should be used to avoid physical damage and minimize electrical noise. For instance, avoid routing cables near high-voltage wires. Do not route cables along floors or walkways where they be stepped on or become contaminated. Shielded cables should have the shield grounded at one end only, normally at the instrumentation end.

**STEP 5:** Finally, connect the remaining cable end to the signal conditioner or readout device. To dissipate charge that may have accumulated in the cable short the signal to ground prior to attachment.

## 6.0 POWERING

All ICP® sensors require constant current excitation for proper operation. For this reason only use approved constant-current sources. A typical system schematic is shown in Figure 11.



**Figure 11.** Typical System Schematic

The power supply consists of a regulated 18 to 30 VDC source. In general, battery-powered devices offer versatility for portable, low-noise measurements, whereas line-powered units provide the capability for continuous monitoring. This power is regulated by a current-limiting circuit, which provides the constant-current excitation required for proper operation of sensors with integral electronics.

**Note:** Under no circumstances should a voltage be supplied to an ICP® accelerometer without a current-regulating diode or equivalent electrical circuit.

A capacitor at the output stage of the device removes the sensor output bias voltage from the measurement signal. This provides a zero-based, AC-coupled output compatible with most standard readout devices.

Today, many FFT analyzers, data acquisition modules, and data collectors have constant-current excitation for direct use with ICP® sensors. However, before using this feature, check that the supply voltage and constant current are adequate for use with your sensor. Please contact the respective signal conditioner manufacturer or check the product manual for more information.

## 7.0 OPERATING

After completing the system setup, switch on the conditioner, the meter (or LED) and allow the sensor to power up. If a faulty condition is monitored, first check all system connections, then check the functionality of the cable and signal conditioner. If


the system still does not operate properly, consult an IMI Application Engineer.

**Note:** Always operate the accelerometer within the limitations listed on the Specification Sheet of your sensor. Operating the device outside of its parameters can cause temporary or permanent damage to the sensor.

## 8.0 ACCELEROMETER CALIBRATION

**Note:** It is good measurement practice to verify the performance of each accelerometer before and after each measurement.

Accelerometers are precision measuring instruments. They are highly engineered to provide accurate electrical signals representative of the vibration being monitored. Each sensor is calibrated by comparison to a known acceleration level. Some calibrations include frequency response curves, resonant frequency measurements, transvers sensitivity, and many other valuable tests. Applications requiring a high degree of accuracy or those in plants requiring certification and traceability require full calibration test results.



**Figure 12.** Typical Calibration Certificate

Some applications have much less stringent requirements for calibration certification. Simple sensitivity measurements at a single frequency may be sufficient; operational verification and certificates of conformance to published specifications may satisfy many plants' calibration needs. Reducing the final calibration requirements reduces the cost of manufacturing the sensor and should lower the price for predictive maintenance users.

Periodic recalibration may be required by plants with strict certification and traceability requirements. It is always recommended that the user has the sensor recalibrated periodically, particularly if the sensor has experienced a very high shock level or extreme temperatures for extended periods of time. Some plants develop in-house calibration capabilities for periodically verifying the performance of accelerometers. Products are available that provide a set 1 g-acceleration level at a fixed frequency for quick sensor checking.

For these reasons, it is recommended that a recalibration cycle be established for each accelerometer. This schedule is unique and is based on a variety of factors, such as extent of use, environmental conditions, accuracy requirements, trend information obtained from previous calibration records, contractual regulations, frequency of “cross-checking” against other equipment, manufacturer recommendation, and any risk associated with incorrect readings. International standards, such as ISO 10012-1, provide insight and suggested methods for determining recalibration intervals for most measuring equipment. With the above information in mind and under “normal” circumstances, a conservative suggestion of 12 to 24 month recalibration cycle for most piezoelectric accelerometers is advised.

### 8.1 SENSOR CALIBRATION


Accelerometer recalibration services are typically performed by IMI’s internal metrology laboratory. (Other international and private laboratories are also available.) The IMI laboratory is certified to ISO 9001, complies with ISO 10012-1 (and former MIL-STD-45662A), and uses equipment directly traceable to NIST. This assures an accurate calibration of relevant specifications.

The following includes a broad overview of the Back-to-Back Calibration technique normally used when calibrating accelerometers. This technique provides a quick and easy method for determining the sensitivity of a test accelerometer over a wide frequency range.

### 8.2 BACK-TO-BACK CALIBRATION THEORY


Back-to-back calibration is perhaps the most common method for determining the sensitivity of

piezoelectric accelerometers. This method relies on a simple comparison to a previously calibrated accelerometer, typically referred to as a reference standard, as shown in Figure 12.



**Figure 12.** Reference Standard Accelerometer

These high-accuracy devices, which are directly traceable to a recognized standards laboratory, are designed for stability, as well as configured to accept a test accelerometer. By mounting a test accelerometer to the reference standard and then connecting this combination to a suitable vibration source, it is possible to vibrate both devices and compare the data as shown in Figure 13. (Test set-ups may be automated and vary, depending on the type and number for accelerometers being calibrated.)




**Figure 13.** Typical Back-to-Back Calibration System

Because the acceleration is the same on both sensors, the ratio of their outputs ( $V_T/V_R$ ) must also be the ratio of their sensitivities. With the sensitivity of the reference standard ( $S_R$ ) known, the exact sensitivity of the test sensor ( $S_T$ ) is easily calculated by using the following equation:

$$S_T = S_R \left( \frac{V_T}{V_R} \right)$$


By varying the frequency of the vibration, the sensor may be calibrated over its entire operating frequency range. The typical response of an unfiltered accelerometer is shown in Figure 14.



**Figure 14.** Typical Test Accelerometer Response


## 9.0 TROUBLESHOOTING

Piezoelectric sensors are dynamic measuring equipment. They use piezoelectric sensing elements to convert or transduce the mechanical phenomena to an electrical signal. The mechanical parameter may be force, pressure or vibration. The raw electrical signal from a piezoelectric charge element is a high impedance signal. This charge signal is normally converted to a low impedance voltage signal by either an external charge amplifier or an external voltage amplifier. The cables between the charge sensor and the amplifier must be high quality, low noise cable and must be kept as short as possible. Figure 15 shows a typical high impedance system.



**Figure 15.** High Impedance System Connection


Internally amplified sensors employ miniature amplifiers to convert the high impedance charge signal into a low impedance voltage signal. These amplifiers are internal to the sensor, and therefore, do not require low noise cables or external amplifiers. These amplifiers have set gain so that output sensitivities are standardized.



**Figure 16.** Sensor with Integral Electronics System Connector

ICP® sensors are two-wire sensors. They are powered with a constant current DC source. The power supply is typically 18 to 30 volts DC current limited via a constant current between 2 and 20 mA. Typical battery operated supplies offer 2mA of constant current to extend battery life while continuous monitoring systems offer more current in order to drive longer cables. Figure 16 shows a typical system for a sensor with integral electronics.


The signal output of a sensor with integral electronics is a low impedance voltage signal proportional to the dynamic measurement such as force, pressure, or vibration. This voltage signal is carried on a DC bias voltage. The AC dynamic signal is superimposed on the DC bias voltage and is allowed to swing between the supply voltage and ground as shown in Figure 17. Unlike an operational amplifier that requires a plus and minus supply and allows the signal to “ride” on ground and “swing” between the plus and minus “rails,” the sensor with integral electronics requires the output signal to be DC biased.



**Figure 17.** Sensor DC Bias Voltage

This DC bias voltage is an excellent diagnostic tool. The voltage provides a means of verifying that the amplifier is “turned on.” Typical input/output power supplies will block this DC bias voltage at the output via a blocking capacitor in order to AC couple the signal to readout devices. By “teeing” off the input into a DC volt meter, as shown in Figure 18, the bias voltage can be measured.

While measuring the supply voltage, the bias voltage can be measured after the sensor is plugged in. If the meter stays at supply, something in the system is open or not connected. If the meter reads “0,” something in the system is shorted. If the meter reads within the bias voltage range of the sensor, then the sensor and cabling are functioning properly.



**Figure 18.** DC Bias Voltage Measurement

### 10.0 REPAIR/RETURN PROCEDURE

Because of the nature of most IMI instrumentation, field repair is typically NOT recommended and may void any warranty. If factory service is required, contact IMI for a **RETURN MATERIAL AUTHORIZATION (RMA)** number prior to sending equipment to the factory. Please have information available, such as model and serial number. Also, to insure efficient service, be sure to include a written description of the symptoms and problems with the equipment to a local sales representative or distributor, or contact IMI if none are located in your area.

Customers outside the U.S. should consult their local IMI distributor for information on returning equipment. For exceptions, please contact the International Sales department at IMI to request shipping instructions and an

RMA. For assistance, please call **(716) 684-0003**, or fax us at **(716) 684-3823**. You may also receive assistance via e-mail at [imi@pcb.com](mailto:imi@pcb.com) or visit our website at [www.pcb.com](http://www.pcb.com).


### 11.0 CUSTOMER SERVICE/WARRANTY

IMI, a division of PCB Piezotronics, guarantees **Total Customer Satisfaction**. If, at any time, for any reason, you are not completely satisfied with any IMI product, IMI will repair, replace or exchange it at no charge. You may also choose to have your purchase price refunded.

IMI instrumentation is warranted against defective material workmanship for 1 year unless otherwise expressly specified. Damage to instruments caused by incorrect power or misapplication, is not covered by warranty. *If there are any questions regarding power, intended application, or general usage, please consult with your local sales contact or distributor.* Batteries or expendable hardware items are not covered by warranty.

IMI offers to all customers, at no charge, 24-hour phone support. This service makes product or application support available to our customers, day or night, seven days a week. When unforeseen problems or emergency situations arise, call the **IMI Hot Line at (716) 684-0003**, and an application specialist will assist you.

## Cable Driving Nomograph



|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |                                                  |                       |                                 |                               |
|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------|-----------------------|---------------------------------|-------------------------------|
| Model Number<br>607A11                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      | PLATINUM SWIVELER® INDUSTRIAL ICP® ACCELEROMETER |                       |                                 | Revision: K<br>ECN #: 56388   |
| <b>Performance</b>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |                                                  | <b>ENGLISH</b>        | <b>SI</b>                       | <b>OPTIONAL VERSIONS</b>      |
| Optional versions have identical specifications and accessories as listed for the standard model except where noted below. More than one option may be used.                                                                                                                                                                                                                                                                                                                                                                                |                                                  |                       |                                 |                               |
| <b>EX</b> - Hazardous Area Approval- contact factory for specific approvals                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |                                                  |                       |                                 |                               |
| <b>M</b> - Metric Mount<br>Supplied Accessory: Model M080A159A Mounting stud, 1/2-20 to M6 x 1 (1) replaces Model 080A156                                                                                                                                                                                                                                                                                                                                                                                                                   |                                                  |                       |                                 |                               |
| <b>TO</b> - Temperature Output                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |                                                  |                       |                                 |                               |
| Sensitivity(± 15 %)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |                                                  | 100 mV/g              | 10.2 mV/(m/s <sup>2</sup> )     | Temperature Output Range      |
| Measurement Range                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |                                                  | ± 50 g                | ± 490 m/s <sup>2</sup>          | Temperature Scale Factor      |
| Frequency Range(± 3 dB)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |                                                  | 30 to 600,000 cpm     | 0.5 to 10,000 Hz                | Electrical Connector          |
| Resonant Frequency                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |                                                  | 1,500 kcpm            | 25 kHz                          | Electrical Connections(Red)   |
| Broadband Resolution(1 to 10,000 Hz)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |                                                  | 350 µg                | 3,434 µm/sec <sup>2</sup>       | Electrical Connections(Black) |
| Non-Linearity                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |                                                  | ± 1 %                 | ± 1 %                           | Electrical Connections(White) |
| Transverse Sensitivity                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |                                                  | ≤ 7 %                 | ≤ 7 %                           | Temperature Output            |
| <b>Environmental</b>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |                                                  |                       |                                 |                               |
| Overload Limit(Shock)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |                                                  | 5,000 g pk            | 49,050 m/s <sup>2</sup> pk      |                               |
| Temperature Range                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |                                                  | -65 to +250 °F        | -54 to +121 °C                  |                               |
| Temperature Response                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |                                                  | See Graph             | See Graph                       |                               |
| Enclosure Rating                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |                                                  | IP68                  | IP68                            |                               |
| <b>Electrical</b>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |                                                  |                       |                                 |                               |
| Settling Time(within 1% of bias)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |                                                  | ≤ 2 sec               | ≤ 2 sec                         |                               |
| Discharge Time Constant                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |                                                  | ≥ 0.3 sec             | ≥ 0.3 sec                       |                               |
| Excitation Voltage                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |                                                  | 18 to 28 VDC          | 18 to 28 VDC                    |                               |
| Constant Current Excitation                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |                                                  | 2 to 20 mA            | 2 to 20 mA                      |                               |
| Output Impedance                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |                                                  | < 150 Ohm             | < 150 Ohm                       |                               |
| Output Bias Voltage                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |                                                  | 8 to 12 VDC           | 8 to 12 VDC                     |                               |
| Spectral Noise(10 Hz)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |                                                  | 8 µg/√Hz              | 78.5 (µm/sec <sup>2</sup> )/√Hz |                               |
| Spectral Noise(100 Hz)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |                                                  | 5 µg/√Hz              | 49.1 (µm/sec <sup>2</sup> )/√Hz |                               |
| Spectral Noise(1 kHz)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |                                                  | 4 µg/√Hz              | 39.2 (µm/sec <sup>2</sup> )/√Hz |                               |
| Electrical Isolation(Case)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |                                                  | > 10 <sup>8</sup> Ohm | > 10 <sup>8</sup> Ohm           |                               |
| <b>Physical</b>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |                                                  |                       |                                 |                               |
| Size (Hex x Height)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |                                                  | 9/16 in x 0.97 in     | 14 mm x 24.6 mm                 |                               |
| Weight(without cable)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |                                                  | 1.1 oz                | 31 gm                           |                               |
| Mounting                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |                                                  | Stud                  | Stud                            |                               |
| Mounting Thread                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |                                                  | 1/4-28 Male           | 1/4-28 Male                     |                               |
| Mounting Torque(Stud)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |                                                  | 3 to 4 ft-lb          | 4.1 to 5.4 Nm                   |                               |
| Mounting Torque(hex nut)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    |                                                  | 2 to 3 ft-lb          | 2.7 to 4.1 Nm                   |                               |
| Sensing Element                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |                                                  | Ceramic               | Ceramic                         |                               |
| Sensing Geometry                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |                                                  | Shear                 | Shear                           |                               |
| Housing Material                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |                                                  | Stainless Steel       | Stainless Steel                 |                               |
| Sealing                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |                                                  | Welded Hermetic       | Welded Hermetic                 |                               |
| Electrical Connector                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |                                                  | Molded Integral Cable | Molded Integral Cable           |                               |
| Electrical Connection Position                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |                                                  | Side                  | Side                            |                               |
| Cable Length                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |                                                  | 10 ft                 | 3.0 m                           |                               |
| Cable Type                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |                                                  | Polyurethane          | Polyurethane                    |                               |
| <div><div><div>CE</div><div>UK</div><div>CA</div></div><div><div>Typical Sensitivity Deviation vs Temperature</div><div><div>Sensitivity Deviation (%)</div><div>Temperature (°F)</div></div></div></div> <div><div><div></div><div></div></div><div>Intertek</div></div> <div>All specifications are at room temperature unless otherwise specified.<br/>In the interest of constant product improvement, we reserve the right to change specifications without notice.<br/>ICP® is a registered trademark of PCB Piezotronics, Inc.</div> |                                                  |                       |                                 |                               |
| <b>NOTES:</b>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |                                                  |                       |                                 |                               |
| [1]Conversion Factor 1g = 9.81 m/s <sup>2</sup> .                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |                                                  |                       |                                 |                               |
| [2]Typical.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |                                                  |                       |                                 |                               |
| [3]Zero-based, least-squares, straight line method.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |                                                  |                       |                                 |                               |
| [4]Measured with mounting stud.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |                                                  |                       |                                 |                               |
| [5]1/4-28 has no equivalent in S.I. units.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |                                                  |                       |                                 |                               |
| [6]1/8" hex Allen key required for English version, 3mm hex Allen key required for metric version.                                                                                                                                                                                                                                                                                                                                                                                                                                          |                                                  |                       |                                 |                               |
| [7]Stud torque must exceed sensor hex nut torque to ensure proper dismantling.                                                                                                                                                                                                                                                                                                                                                                                                                                                              |                                                  |                       |                                 |                               |
| [8]Twisted shielded pair.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |                                                  |                       |                                 |                               |
| [9]See PCB Declaration of Conformance PS023 or PS060 for details.                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |                                                  |                       |                                 |                               |
| [10]See Model's "Instructions For Use" (IFU) for North American Conformity and Certification Statements.                                                                                                                                                                                                                                                                                                                                                                                                                                    |                                                  |                       |                                 |                               |
| <b>SUPPLIED ACCESSORIES:</b>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |                                                  |                       |                                 |                               |
| Model 080A156 Mounting Base (1)<br>Model ICS-2 NIST-traceable single-point amplitude response calibration at 6000 cpm (100 Hz) for each axis (1)                                                                                                                                                                                                                                                                                                                                                                                            |                                                  |                       |                                 |                               |
| Entered: ND                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 | Engineer: NJF                                    | Sales: JL             | Approved: NJF                   | Spec Number:                  |
| Date: 04/20/2026                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            | Date: 04/20/2026                                 | Date: 04/20/2026      | Date: 04/20/2026                | 12650                         |
| <div><div></div><div>Phone: 800-959-4464<br/>Fax: 716-684-3823<br/>E-Mail: imi@pcb.com</div></div> <div>A PCB PIEZOTRONICS DIV.<br/>3425 Walden Avenue, Depew, NY 14043</div>                                                                                                                                                                                                                                                                                                                                                               |                                                  |                       |                                 |                               |

2

1

PCB Piezotronics Inc. claims proprietary rights in the information disclosed herein. Neither it nor any reproduction thereof will be disclosed to others without the written consent of PCB Piezotronics Inc.

# REVISIONS

| REV | DESCRIPTION         | DIN   |
|-----|---------------------|-------|
| E   | ADDED RELATED BLOCK | 44208 |

## RELATED DRAWING

NO MODIFICATIONS PERMITTED WITHOUT THE APPROVAL OF THE AUTHORIZED PERSON

12441

Ø.625 [15.88]

MOLDED INTEGRAL CABLE  
TERMINATING IN BLUNT CUT  
10 FT [3 M] FROM APPLICATION

1.58 [40.1]

.98 [24.9]

WHITE: SIG/POWER

BLACK: GROUND

$\frac{9}{16}$  [14] HEX

$\frac{1}{8}$  HEX ALLEN KEY REQUIRED

MOUNTING STUD  
MODEL 080A156  
(SUPPLIED)

1/2-20 UNF - 2A

1/4-28 UNF - 2A

### UNLESS OTHERWISE SPECIFIED TOLERANCES ARE:

#### DIMENSIONS IN INCHES

DECIMALS XX ±.03  
XXX ±.010

ANGLES ± 2 DEGREES

FILLETS AND RADII  
.003 - .005

#### DIMENSIONS IN MILLIMETERS [IN BRACKETS]

DECIMALS X ± 0.8  
XX ± 0.25

ANGLES ± 2 DEGREES

FILLETS AND RADII  
0.07 - 0.13

#### DRAWN

BB 5/15/15

#### CHECKED

ECB 5/15/15

#### ENGINEER

GGG 5/15/15

#### TITLE

OUTLINE DRAWING  
MODEL 607 SERIES  
ACCELEROMETER

**PCB PIEZOTRONICS**

3425 WALDEN AVE. DEPEW, NY 14043  
(716) 684-0001 E-MAIL: sales@pcb.com

CODE  
IDENT. NO.  
52681

DWG. NO.

12441

SCALE: 2.5X

SHEET 1 OF 1

2

1

18551

PCB Piezotronics Inc. claims proprietary rights in the information disclosed hereon. Neither it nor any reproduction thereof will be disclosed to others without the written consent of PCB Piezotronics Inc.

| REVISIONS |                                   |       |
|-----------|-----------------------------------|-------|
| REV       | DESCRIPTION                       | DIN   |
| B         | ADDED METRIC MOUNTING INFORMATION | 43341 |

METRIC MOUNTING HOLE PREPARATION:

DRILL Ø.199[Ø5.05]  $\nabla$ .300[7.62] MIN 1

TAP M6 X 1-6g  $\nabla$ .200[5.08] MIN

ENGLISH MOUNTING HOLE PREPARATION:

DRILL Ø.218[Ø5.54]  $\nabla$ .300[7.62] MIN 1

TAP 1/4-28 UNF-2B  $\nabla$ .200[5.08] MIN





FIG 1: A 1/8" HEX ALLEN KEY IS REQUIRED FOR THE ENGLISH MOUNTING STUD. A 3MM HEX ALLEN KEY IS REQUIRED FOR THE METRIC MOUNTING STUD. APPLY SILICONE GREASE TO ALL MOUNTING SURFACES (SEE ARROWS FIG 1 & 2)





FIG 2: TIGHTEN THE MOUNTING STUD USING THE ALLEN KEY. TORQUE THE MOUNTING STUD TO WITHIN 3 TO 4 FT-LBS. (4.1 TO 5.4 Nm)





FIG 3: THREAD THE SENSOR'S HEX NUT ONTO THE MOUNTING STUD. POSITION THE CABLE OR CONNECTOR TO THE DESIRED LOCATION AND HAND TIGHTEN THE HEX NUT.





FIG 4: TIGHTEN THE HEX NUT USING A TORQUE WRENCH TO WITHIN 2 TO 3 FT-LBS (2.7 TO 4.1 Nm) WHILE HOLDING THE CABLE OR CONNECTOR IN THE DESIRED LOCATION.




FIG 5: IF FOR ANY REASON THE MOUNTING STUD DOES NOT DISENGAGE FROM THE SENSOR, USE A FLAT HEAD SCREW DRIVER TO HOLD THE STUD WHILE TURNING THE HEX NUT COUNTERCLOCKWISE WITH A WRENCH.

3.) FOR BEST RESULTS, PLACE A THIN LAYER OF SILICONE GREASE (DOW CORNING #4 OR EQUIVALENT) ON INTERFACE PRIOR TO MOUNTING.

2 MOUNTING SURFACE SHOULD BE FLAT TO WITHIN .001 [0.03] TIR WITH A MINIMUM 63 [1.6] FINISH FOR BEST RESULTS.

1 DRILL PERPENDICULAR TO MOUNTING SURFACE TO WITHIN  $\pm 1^\circ$

| UNLESS OTHERWISE SPECIFIED TOLERANCES ARE: |                                              | DRAWN                                                 |         | CHECKED |         | ENGINEER |         |  <b>PCB PIEZOTRONICS™</b><br>3425 WALDEN AVE. DEPEW, NY 14043<br>(716) 684-0001 E-MAIL: sales@pcb.com |                       |
|--------------------------------------------|----------------------------------------------|-------------------------------------------------------|---------|---------|---------|----------|---------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------|
| DIMENSIONS IN INCHES                       | DIMENSIONS IN MILLIMETERS<br>[ IN BRACKETS ] | JDM                                                   | 10/9/14 | ECB     | 10/9/14 | DRK      | 10/9/14 |                                                                                                                                                                                            |                       |
| DECIMALS   XX ±.01<br>XXX ±.005            | DECIMALS   X ±.03<br>XX ±.013                | TITLE<br><br>INSTALLATION DRAWING<br>MODEL 607 SERIES |         |         |         |          |         |                                                                                                                                                                                            |                       |
| ANGLES ± 2 DEGREES                         | ANGLES ± 2 DEGREES                           |                                                       |         |         |         |          |         |                                                                                                                                                                                            |                       |
| FILLETS AND RADII<br>.003 - .005           | FILLETS AND RADII<br>0.07 - 0.13             |                                                       |         |         |         |          |         | CODE<br>IDENT. NO.<br>52681                                                                                                                                                                | DWG. NO.<br><br>18551 |
|                                            |                                              |                                                       |         |         |         |          |         | SCALE:   FULL                                                                                                                                                                              | SHEET   1 OF 1        |

## SIL Declaration of Conformity

Functional safety according to IEC 61508

Manufacturer: PCB Piezotronics  
 3425 Walden Avenue  
 Depew, NY 14043 USA

PCB Piezotronics declares as manufacturer, that the vibration transmitters:

- 602 Series (XX)602yzzz/aaa
- 603 Series (XX)603yzzz/aaa
- 606 Series (XX)606yzzz/aaa
- 607 Series (XX)607yzzz/aaa
- 608 Series (XX)608yzzz/aaa

(XX) Options include one or more of the following:

- EX – Approved for Hazardous Locations
- M – Metric Mounting Hardware
- TO – Dual Output (Vibration/Temperature)

Note: "yzzz" completes the model, "aaa" indicates cable length (if applicable)

Is hardware suitable for use in safety-instrumented systems according to IEC 61508, if the safety instructions and the following parameters are observed:

| Parameter                                              | 60x Series*           | EX60x Series*         |
|--------------------------------------------------------|-----------------------|-----------------------|
| SIL                                                    | 2                     | 2                     |
| Proof Test Interval (Annual)                           | 8,760 h               | 8,760 h               |
| Device Type                                            | B                     | B                     |
| HFT                                                    | 0                     | 0                     |
| SFF                                                    | 79.59%                | 79.59%                |
| $PFD_{AV}^1$                                           | $7.45 \times 10^{-5}$ | $7.45 \times 10^{-5}$ |
| $\lambda_{du} \times 10^{-6}$                          | 0.3348                | 0.3348                |
| SIL Capability (Low Demand Mode)                       | 2                     | 2                     |
| SIL Capability (Continuous Demand Mode)                | 2                     | 2                     |
| MTTF <sup>2</sup>                                      | 9.5 y                 | 9.5 y                 |
| 1. The values comply with SIL2 according to ISA S84.01 |                       |                       |
| 2. According to Siemens SN29500 and Proven In Use data |                       |                       |

\* With or without the M (metric) option

The PCB sensor hardware is suitable for inclusion in Safety Instrumented Systems (SIS) that are designed using IEC 61511 (for the process industry sector), IEC 62061 (safety of machinery), EN 50129 (railway applications), and ISO 26262 (automotive industry).

Note: The use of SIL Hardware in specific safety standard application may apply different number of sequences or definitions to those in IEC 61508.

July 2, 2019

PCB Piezotronics Authorized Representative:

Carrie Termin  
 Regulatory Affairs and Product Certification Specialist



**PCB PIEZOTRONICS, INC. — CORPORATE HEADQUARTERS**

3425 Walden Avenue, Depew, New York 14043-2495 USA

Phone: 716-684-0001 Fax: 716-684-0987

E-mail: info@pcb.com

Web site: www.pcb.com

**AS9100 and ISO9001 Certified**  
**ISO17025 Accredited**

# INTERTEK ASSURANCE SAFETY INTEGRITY LEVEL SUMMARY REPORT **60X PCB SIL SENSOR RATING**

**CLIENT NAME**

PCB Piezotronics, Inc.  
3425 Walden Ave  
Depew, NY 14043-2417

**REPORT NO**

103685042CSLT-003

**COMPILED BY**




Ashton D. Hainge, CFSP, PMP

**PROJECT NAME**

G103685042

**DATE**

02 April 2019





## PCB FUNCTIONAL SAFETY SIL SUMMARY AND RESULTS

### Summary

This report details the results of the reliability analysis performed on the PCB Piezotronics ICP Sensor model 60X series. Design changes from this documentation package would need to be evaluated for the impact on the reliability characteristics. These results are based on the following PCB Piezotronics documentation:

1. Electrical schematic 23402-NR
2. 603C01 MTTF Calculation
3. 602C11 – 602D11 MTTF Calculation
4. 607-608 MTTF Calculation
5. Manual of 603C01

### Results

The results from the FMEA are given below for the ICP Sensor model 60X Series:

| Name                                    | Result                |
|-----------------------------------------|-----------------------|
| Architecture                            | 1001                  |
| Proof test interval (Annual)            | 8,760 h               |
| PFD <sub>avg</sub>                      | 7.45x10 <sup>-5</sup> |
| SFF                                     | 79.59%                |
| HFT                                     | 0                     |
| SIL Capability (Low Demand Mode)        | 2                     |
| SIL Capability (Continuous Demand Mode) | 2                     |
| Architecture                            | 1001                  |

**PCB Sensor Product Meets SIL 2 Capability**



| Name                                               |                               | Result |
|----------------------------------------------------|-------------------------------|--------|
| Safe Detected failure rate                         | $\lambda_{SD} \times 10^{-6}$ | 0.019  |
| Safe Undetected failure rate                       | $\lambda_{SU} \times 10^{-6}$ | 0.013  |
| Dangerous Detected failure rate                    | $\lambda_{DD} \times 10^{-6}$ | 0.033  |
| Dangerous Undetected failure rate                  | $\lambda_{DU} \times 10^{-6}$ | 0.017  |
| Average frequency of a dangerous failure on demand | $PFH \times 10^{-6}$          | 0.796  |

#### Type B components: 60X Series

The safety relevant parameter  $PFD_{avg}$  is in compliance with the corresponding requirements for SIL 2 according to IEC 61508<sup>1</sup>. The safety relevant parameters HFT and SFF are in compliance with the corresponding requirements for SIL 1 according to IEC 61508. The user should consider, that the hardware fault tolerance of all inspected devices is zero and that a single fault can lead to a dangerous failure. Even though  $PFD_{avg}$  has the range of SIL 4, the hardware fault tolerance limits the capability to SIL 2.

Senior Consultant,

Ashton Hainge, Intertek  
CFSP, PMP

<sup>1</sup> The assessment results described in this report only refer to the safety-related parameters PFD avg, HFT, and SFF according to IEC 61508.

This report does not make any statements, that the manufacturer meets all other requirements of the above cited standards for hardware, software, documentation, management of functional safety, verification, and validation.

This report does not imply that the examined pressure sensors have been certified for functional safety by the assessor according to IEC 61508 or any other standards.

The sensors are only one part of a complete safety function. It is at the responsibility of the end-user to prepare and to apply an extensive reliability model, that brings out the complete safety function and that meets all requirements of the claimed SIL level according to IEC 61508.